

Phased Array X Type Digital TV Antenna

UHF (21-50) 36 Elements

O2MM-MDU36



For the Best

The O2MM-MDU36 does a fantastic job of filtering out interference with the help of its advanced 4G/5G LTE filter. In addition, the unit can get a maximum gain of 12dB via a phased array setup, which in turn allows for optimum reception when receiving UHF Channels 28-51.

Features and Benefits

- » 694MHz low pass 4G LTE filter
> 30dB at 750 MHz
- » Attractive retail packaging
- » Receives UHF Channels 21-50
- » Also available in 5 pack
(O2MM-MDU36-BULK)

O2MM-MDU36 Specifications

| | |
|------------------|------------------------|
| Elements | 36 |
| Channels | (21-50) |
| Frequency Range | 470-694MHz |
| Maximum Gain | 12dB |
| Front/Back Ratio | >18dB |
| Balun Type | 'F' Type PCB 4G Filter |
| Packing Unit | Inner 1, Outer 5 |

